

Technical Bulletin

Fixing the printer bug in the VZ-editor assembler.

Below is a patch to enable your editor assembler to list its source code. As stated in the manual using option C.

First enter Insert mode by entering 'I'. Then set code origin by entering 'O'. Now type in the below program, pressing RETURN at the end of each line.

```

001      LD  BC,0CH      ;Size of transfer is 12 bytes.
002      LD  HL,LOOP    ;Point to new printer routine
003      LD  DE,8F54H   ;Point to editor assembler print out
004      LDIR           ;Transfer routine to editor assembler
005      JP  7B00H      ;Return control to editor assembler
006 LOOP IN  A,(00H)   ;Load printer status
007      BIT 0,A       ;Check ready bit
008      JR  NZ,LOOP    ;Repeat LOOP if not ready
009      LD  A,C        ;Load Accumalator with print data
010      OUT (0EH),A    ;Output data to printer port
011      OUT (0DH),A    ;Another port for an early interface
012      RET           ;Get next character

```

Now assemble the program by entering 'A'. Now RUN the program by entering 'R' then press 'Y' to verify you wish to execute the program. Finish up by deleting the program by entering 'D*'. Your editor assembler may list programs now, just by selecting option 'C'. (enter 'SC').


There appear to be two
versions of EDASM, V1.1 & V1.2

For V1.2 line 3 above
should be.

LD DE, 8F57H

(Letter from Jamie Perry 23/6/86)

Yours sincerely



Jamie PERRY